

3G modem wiki

Huawei AT-commands

note: Some devices like the Huawei K3715 seem to require AT-commands to be typed in capital letters!

There are a couple of options for disabling and re-enabling the following USB-components of Huawei USB-modems:

- modem (**M**)
- NAND-flashmemory drive (**CD**)
- microSD-drive (**SD**)
- PC UI interface (**UI**)
- network adaptor (**N**)
- smartcard (**SC**)

To disable or re-enable those components run the following AT-command, where **n** is one of the numbers from the table below:

AT^U2DIAG=**n**

On some models it is possible to read the present value of the parameter **n** by sending command:

AT^U2DIAG?

n	M	CD	SD	UI	N	SC	remarks	supported by	not supported by
0	+			+				E160, E1750	
1	+	+							
3	+			+		+	won't work on devices without SC*		
5		+		+	+		won't work on devices without N*		
9		+			+	+	won't work on devices without N & SC*		
10	+	+				+	won't work on devices without SC*		
12		+		+	+		won't work on devices without N*		
255	+	+	+	+	?	?	reset to factory defaults	E160, E160E, K3565, K3715	E176, E1762, E1750, E173
256	+		+	+			for most devices: everything enabled except the flashmemory; microSD-drive will be available under Windows even without drivers installed	E160, E160E, E173, E1750, E1762, K3565, K3715	E176
257	+	+	+						
259	+		+	+		+	won't work on devices without SC*	E173u-2, E176	
261		+	+		+	+	won't work on devices without N & SC*		
265		+	+		+	+	won't work on devices without N & SC*		
266	+	+	+			+	won't work on devices without SC*		
267		+	+		+		won't work on devices without N*		
268	+	+	+	+			won't work on devices without N*	E1750, K3565, E173	
276	+	+	+	+	+	?	reset to factory defaults	E1762, K3565, K3765, E173, E1750	

*) note: Smartcard (SC) and network adaptor (N) are not present in many Huawei devices. Using an AT-command that activates SC or N on a device without these components, will result in errors and so will be noneffective.

Modems supporting **AT^U2DIAG?** command: E173, E1750, E160E

Modems not supporting **AT^U2DIAG?** command: E160, K3565

Also on some models it is possible to display a list of devices present in a USB-stick, by sending a command:

AT^GETPORTMODE



Latest page update: made by [Chris_M](#) , Jun 7 2014, 8:03 PM EDT ([about this update](#) - [complete history](#))

[Chris_M](#)

Keyword tags: None



[Share this](#)



[Threads for this page](#)

Started By	Thread Subject	Replies	Last Post
kirolos	help me plz for unlocker e177u-1 zain sudan Thread started: Oct 18 2013, 7:24 AM EDT Watch help me plz for unlocker e177u-1 zain sudan Keyword tags: None Show Last Reply	1	Mar 1 2014, 10:10 AM EST by Mohammed_albager
jjsg	Vodfaone Huawei k3765 OR Huawei E1762 Thread started: Dec 11 2012, 3:09 AM EST Watch I tryed disable the autorun and micro-SD reader function of the modem by using AT commands from the above table. BUT DON`T WORKS, always the message COMMAND NOT SUPPORT, so what are the right commands for this PEN? BR:JG Keyword tags: None	0	Dec 11 2012, 3:09 AM EST by jjsg
Privileged_User	AT command documentation for ZTE MF 191 modem Thread started: Oct 3 2012, 11:03 AM EDT Watch Hi, looking for AT command documentation for ZTE MF 191 modem. Thanks. Keyword tags: None	0	Oct 3 2012, 11:03 AM EDT by Privileged_User

Showing 3 of 16 threads for this page - [view all](#)