

3G modem wiki

Huawei E160 (E160G, E160E, E160X)**Specifications**

manufacturer:	Huawei	Huawei	Huawei
model:	E160	E160G	E160E, E160X
interface:	USB 2.0 (A plug)	USB 2.0 (A plug)	USB 2.0 (A plug)
GSM frequency bands:	850, 900, 1800, 1900	850, 900, 1800, 1900	850, 900, 1800, 1900
UMTS frequency bands:	2100	2100	900, 2100
HSDPA:	3,6 MBit/s	3,6 MBit/s	3,6 MBit/s
HSUPA:	-	-	-
EDGE:	236,8 KBit/s	236,8 KBit/s	236,8 KBit/s
GPRS:	57,6 KBit/s	57,6 KBit/s	57,6 KBit/s
CSD:	?	?	?
connector for ext. antenna:	+	+	+
connector type:	CRC9	CRC9	CRC9
internal antenna diversity:	+	+	+
voice telephony:	enabled	enabled	enabled
NAND-flashmemory:	+ (32 MB)	+	+
microSD-drive:	+ (up to 8GB)	+ (up to 8GB)	+ (up to 8GB)
hardware version:	CD25TCPU	CD25TCPU	CD25TCPU
chipset:	Qualcomm MSM6246	Qualcomm MSM6246	Qualcomm MSM6246
rebranded versions:	Fonic Surf-Stick (DE) MEDIONmobile Web Stick S4011 (DE) O2 Loop Surf Stick (DE) Tchibo Internet-Stick (DE) A1 (AT)	T-Mobile PrePaid Internet Stick (NL) T-Mobile (DE) 3/Drei/Three (AT) - voice not supported	N24 Surf Stick (DE) Pro7 (DE) Vodafone K3565

Unlocking



unlock codes are available free of charge at <http://a-zgsm.com/huawei.php>

To unlock your device, put in a third-party SIM card, start Mobile Partner and after entering the PIN code, the unlock code will be required.

Debranding

see [debranding Huawei modems](#)

Latest update

- latest dashboard update (will flash onto memory)
[E160G Client Software-WINMACB300D00SP01C03 \(UTPS11.300.05.00.03 MACHOST11.202.08.00.03\) \(For Winxp&2K&Vista &MAC\) \(05010AAG\)](#)  (10395 KB) **27-May-2009**
alternatively try this [inofficial version](#) (especially required for the Vodafone K3565)
- latest firmware update
[11.609.10.00.00.B716](#)  (22940 KB) **1-Jun-2010**

Disable/revive flashdrive

The integrated flashdrive of the E160 can be disabled by executing the following AT-command:

```
at^u2diag=256
```

If your modem answers ERROR, instead you can use command:

```
at^u2diag=0
```

Unfortunately this command will also disable the microSD-drive.

To revive the flashdrive and the microSD-drive execute:

```
at^u2diag=255
```

More at page [Huawei AT-commands](#)

Weblinks

product page of manufacturer:

support page of manufacturer:



Latest page update: made by [periskop](#), May 13 2014, 12:18 PM EDT ([about this update](#) - [complete history](#))

[periskop](#)

Keyword tags: [E160](#) [E160G](#) [E160E](#) [E160X](#) [K3565](#) [unlock code](#) [unlock code for E160](#)



[Share this](#)

Threads for this page

Started By	Thread Subject	Replies	Last Post
Anonymous	Please help me to unlock my Huawei E160 Thread started: May 28 2010, 2:01 AM EDT Watch IMEI : 357943034215913 my email : prabhashana_uom@yahoo.com Keyword tags: E160 E160G E160E E160X K3565 k3565 Show Last Reply	2	Apr 19 2014, 12:10 AM EDT by Saigovind
reubenyenlienyeni	what is the password dashboard E160EUpdate_11_609_10_00_00_B716.zip Thread started: Apr 3 2013, 1:13 AM EDT Watch Please i need the password to permit me upgrate my hauwei e160e modem dashboard version E160EUpdate_11_609_10_00_00_B716.zip Keyword tags: E160 E160G E160E E160X K3565 unlock code unlock code for E160	0	Apr 3 2013, 1:13 AM EDT by reubenyenlienyeni
suwanto	what's the password ? Thread started: Jan 27 2012, 8:05 PM EST Watch when i upgrading firmware from above. there's need password to enter. please help me.. Keyword tags: E160 E160G E160E E160X K3565 unlock code unlock code for E160 Show Last Reply	2	Feb 18 2013, 2:58 AM EST by theorator1430

Showing 3 of 29 threads for this page - [view all](#)

Related Content

[\(what's this?\)](#)

[Please help me to unlock my Huawei E160](#)

[please](#)

[unlock code for huawei E160 IMEI
353871022425885](#)

[Risk E160G change drivers \(already in Crack\)
with E1550 driver \(not ye](#)

[what is the password dashboard
E160EUpdate_11_609_10_00_00_B716.zip](#)

[Vodafone K3565 \(Huawei\) bricked :-\)](#)

[Huawei E160E E1550 E1552 Problem After
Mobile Partner UPGRADE](#)

[what's the password ?](#)

[Huawei E160E update failure](#)

[3network to vodafone](#)